

I.SITE PLUS



The self-reliant transmitter for local alarm systems

I.SITE PLUS is a POCSAG-transmitter for local alarm systems. It is equipped with an in-built backup battery including charging port. The backup battery ensures the possibility to send out alerts in the event of a power failure.

It is controlled via Ethernet LAN (RJ-45) or via the in-built push buttons releasing predefined messages. POCSAG-messages are prepared internally and sent via the transmission unit (1-25 W). Three local digital inputs are available. Messages at the digital inputs are either processed directly as POCSAG-messages or reported as additional status messages of the alarm server.

Multiple I.SITE PLUS can operate in parallel via LAN as long as the radio coverage areas do not overlap.

The Swissphone protocol for integrating the I.SITE PLUS into your solution is available to third-party suppliers.

Key performance features

- » Cost-effective stand-alone application
- » Networking thanks to LAN port
- » Uninterruptable operation mode
- » Parallel operation of multiple I.SITE PLUS transmitters via LAN for asynchronous networks.
- » Self-reliance by in-built push buttons for releasing predefined alerts.
- » ESPA 4.4.4 input protocol

I.SITE PLUS consists of the following four function blocks:

- AC/DC converter
- Backup battery
- Transmission unit
- Controller board

The following product combinations are possible

- I.SITE PLUS in stand-alone operation
- I.SEARCH in combination with I.SITE PLUS

I.SITE PLUS

	Performance features	Technical data
Transmission unit (TX)	Frequency bands (each pre-programmed with up to 35 channels)	VHF 2 m Band: 136-174 MHz
	Transmitting power	1 to 25 W (1 W steps)
	Channel separation	12.5 / 20 / 25 kHz
	POCSAG Transmission rate	512, 1200, 2400 baud
	Antenna port	N-Type (female) 50Ω port for external antenna
	Duty cycle	33% at 25W (@ 55°C)
Interface	LAN	1x RJ-45 (100 Mbps)
	Call log	TAP, ESPA 4.4.4
	Control	PC software or through third-party providers
	Input contacts	Three contact inputs (E1, E2, E3 (open/close)) for triggering messages (edge triggered, potential-free 5 - 15 V, debounced to 100 ms)
	Push buttons	Three highly robust, luminous push-buttons. Stainless steel, > 1 Mio. cycles of operation
Fault status reports	FS01 - FS05	Extensive fault status reports
General	Operating temperature range	-20 °C ... +55 °C
	Input voltage (AC)	90-264 VAC
	Backup battery	12 V / 2,3 Ah (charging port + battery low display + deep discharge protection)
	Power consumption (max., an 230 V)	5 W (stand-by), 75 W (sending at max. 25 W)
	Protection class	IP65
	Dimensions (H x B x T)	400 x 210 x 120 mm
	Weight	7.5 kg (without optional backup battery)
Conformity	Compliance with EU regulations:	Safety EN 60950-1
	Radio Equipment Directive (RED), 2014/53/EU	EMC ETSI EN 301489-1
	RoHS Recast Directive, 2011/65/EU	ETSI EN 301489-5
	WEEE Directive, 2012/19/EU	Radio ETSI EN 300113
	FCC	RoHS EN 50581: 2012 FCC approval

Subject to change without notice

We reserve the right to change the content of this document, either in part or in full, without prior notice. The information in this document refers to the product. All rights reserved. All images and technical drawings used in this document are the property of Swissphone Wireless AG and may not be used without our consent. Company and product names mentioned in this document may be protected by trademark, brand or patent laws.

EN 06/2017 0340318 v2 WEC



Swissphone Wireless AG
Fälmisstrasse 21
CH-8833 Samstagern
Tel.: +41 44 786 77 70
Fax: +41 44 786 77 71
E-Mail: info@swissphone.com



CAPTURE TECHNOLOGIES LTD
1880 LEEK ROAD
STOKE ON TRENT
STAFFORDSHIRE
ST2 7AH
TEL:0843 506 6000